

# Intellia Multisensor Detector EDI-30

Instruction Sheet  
R10074GB0



## **Schneider Electric Fire & Security Oy**

Sokerilinnantie 11 C  
FI-02600 Espoo, Finland  
Tel: +358 10 446 511  
Website: [www.schneider-electric.com](http://www.schneider-electric.com)  
Document number: R10074GB0  
Published: 26.04.2019

© 2018 – Schneider Electric. All Rights Reserved. This information is only to be used as guidance. Subject to changes and errors.

# Contents

<b>1</b>	<b>Intellia Multisensor Detector EDI-30.....</b>	<b>4</b>
1.1	Intellia Fire Detectors .....	4
1.2	Features .....	4
1.2.1	Response setting .....	4
1.2.2	Rejection of transient signals.....	5
1.2.3	Drift compensation .....	5
1.3	Product Codes .....	5

# 1 Intellia Multisensor Detector EDI-30

The Intellia multisensor detector EDI-30 comprises optical smoke and thermistor temperature sensors whose outputs are combined to give the final analogue value. As a result, the multisensor is useful over a wide range of applications and is highly immune to false alarms.

The way in which the signals from the two sensors are combined depends on the response mode selected. The five modes provide response behaviour which incorporates pure heat detection, pure smoke detection and a combination of both.

Mode 5 has no smoke sensitivity at all but gives a pure heat detector response. If the multisensor is used in mode 5, heat detector spacing and coverage should be applied.

The signals from the optical smoke sensing element and the temperature sensor are independent and represent the smoke level and the air temperature respectively in the vicinity of the detector.

## 1.1 Intellia Fire Detectors

Intellia is a range of high-specification, intelligent fire detectors developed to meet the requirements of sophisticated systems. Intellia gives you total reassurance in installations where adaptability to changing conditions and protection against unwanted alarms are paramount. Intellia uses a digital communications protocol.

The Intellia series of products are all compatible with the ALC-board of Esmi Sense FDP and FX panel.

## 1.2 Features

### 1.2.1 Response setting

Each detector in the Intellia range can operate in one of five response modes, any of which can be selected from the Esmi Sense FDP and FX control panel. Each mode corresponds to a unique response behaviour, which can be broadly related to sensitivity to fire.

For ionisation and optical smoke detectors, the modes relate to different combinations of smoke response threshold and response time. For the heat detector, the mode relates to the fixed temperature setting and the sensitivity to rate-of-rise of temperature. For the multisensor, the mode relates to the levels of smoke and heat sensitivity and to the way in which the responses of the two sensors are combined.

The response characteristics of the detectors have been carefully set so that detectors will comply with the requirements of the relevant part of EN54 in all response modes. The mathematical algorithms embedded in the detectors are used to carry out changes in characteristics between modes.

### 1.2.2 Rejection of transient signals

All Intellia detector algorithms are designed to give low sensitivity to very rapid changes in the sensor output, since these are unlikely to be caused by real fire conditions. This is achieved by digital low-pass filtering of the sensor values which optimises the rejection of false alarm sources while maintaining the response to fire.

### 1.2.3 Drift compensation

All Intellia smoke detectors include compensation for sensor drift as part of the internal signal-processing algorithm. The algorithm will compensate for changes in sensor output caused, for example, by dust in the chamber, and will therefore hold the sensitivity at a constant level even with severe chamber contamination. This increased stability is achieved without significantly affecting the detector's sensitivity to fire.

## 1.3 Product Codes

Product	Product codes
EDI-30 Multisensor Detector	FFS0672 0230
EBI-10 Standard Mounting Base	FFS0672 0010
EBI-20 Relay Base	FFS0672 0020