








## Gira Keyless In keypad



Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
 cream white glossy	2605 01	1	235.10	10	4010337051343
 pure white glossy	2605 03	1	235.10	10	4010337051350
 pure white matt	2605 27	1	235.10	10	4010337051374
 anthracite	2605 28	1	238.90	10	4010337051381
 colour aluminium	2605 26	1	243.77	10	4010337051367
 black matt	2605 005	1	235.99	06	4010337037125
 grey matt	2605 015	1	242.82	06	4010337084662

## Features

- Installation in a device box.
- Stand-alone device or in combination with the Gira door communication system.

- For stand-alone operation, the integrated zero-voltage relay contacts are used for switching actions, e.g. for a door opener with its own power supply (e.g. common doorbell transformer).
- Start-up with direct configuration without a PC or programming software.

## Inputs and outputs

- Switching contact: Two relays with zero-voltage 2-way switch contacts, load capacity AC/DC 24 V / 1.6 A.
- Two connections for power supply.
- Keypad as an access control system with a capacitive and therefore wear-free button field.
- Frequently used number combinations cannot be recognised.
- Stand-alone device or in combination with the Gira door communication system as a door call system for buildings with several residential units.
- Special button "C": Deleting an incorrect entry.
- Special button "Key": Direct door opening when the correct code has been entered.
- Special button "Bell": Specific selection of home stations in large facilities.
- Special button "F": Switching functions with switching actuators of the Gira door communication system.
- Homogeneous blue LED illumination of the numbers and special characters at night.
- Master PIN number provided on included sealed safety card if administrator PIN number is lost.
- The keypad can manage up to 255 codes.
- Up to 32-digit codes are possible.
- Audible feedback when button is pressed.
- Three-colour LED status display during programming and operation.
- Warning tone in case of unauthorised removal of the keypad top unit for tamper detection. Tampering circuit with switching actuator in the Gira door communication system.
- The two integrated 2-way switch relays can be assigned two different codes, e.g. Code 1: door opening, Code 2: switching outdoor light.

## Inputs and outputs

- Connection cable connector strip for the Gira door communication system.

---

## Technical data

### Protection type

- |                         |      |
|-------------------------|------|
| - System 55, Gira F100: | IP20 |
| - TX_44:                | IP44 |

### Power supply

- |   |                    |
|---|--------------------|
| - from power supply for door communication: | DC 24 V $\pm$ 10 % |
| - from the door communication system:       | DC 26 V $\pm$ 2 V  |

### Relay

- |                  |                             |
|------------------|-----------------------------|
| - Number:        | 2                           |
| - Contact:       | 1 2-way switch zero-voltage |
| - Load capacity: | AC/DC 24 V / 1.6 A          |

### Connections

- |  |                        |
|--|------------------------|
| - Connection cable for door communication: | 1 x connector strip    |
| - Relay:                                   | 3 screw terminals each |
| - Additional power supply:                 | 2x screw terminals     |

Resistance to EMD:	up to 16 kV
--------------------	-------------

Installation depth:	35 mm
---------------------	-------

Ambient temperature:	-20 °C to +70 °C
----------------------	------------------

## Notes

- Keyless In devices can be connected to the Gira HomeServer using the DCS-IP gateway. This enables intelligent links. In this way, e.g. temporary or one-time access authorisation can be easily granted. All data including access authorisations can be managed centrally and flexibly using the Gira HomeServer.
  - Integration possible in Profile 55.
-