## KNX: Corridor HF Sensor

Sensor with a long and narrow detection developed for KNX system






Aura Light's KNX Corridor HF Sensor is the perfect solution for long detection areas like corridors. Even the smallest movements can be detected by the nearly invisible sensor when the antenna is clapped-in. The movable

antenna makes the sensor flexible for a variety of mounting places. The lighting, heating or ventilation can be controlled by this sensor if it is a part of a KNX Bus. It is a suitable sensor for meeting rooms, offices, restrooms, warehouses or car parks.

- Detection range up to 30 x 6 m at mounting height 2.8 m
- ETS software can be downloaded from auralight.com
- KNX activation programmed through the button on the sensor or by remote control
- Daylight linking function
- Semi- and fully automatic function
- Stepless dimming level, hold time and detection sensitivity
- Remote controlled for professional commissioning
- Available versions: on&off/DALI/DSI/ 1-10V/ AN10<sup>®</sup> /KNX
- Factory Preset for plug & play
- Low convex profile
- Two manual switch inputs
- Remote controlled light scenes
- Designed to be a part of a KNX system








PRODUCT	MWS3-KNX	
Article no.		
TECHNICAL DATA	Depends on region	
	·	
Sensor type	10,525 GHz	
Sensor model	KNX	
Article no.	760195	
Voltage	30V/DC	
Max. load	-	
Max. no. of ballasts	-	
IP class	IP40	
Power consumption passive	23,2 mA	
Power consumption active	23,2 mA	
Operating temperature	-10 °C - +35 °C	
Features		
Detection range	30x6 m / h 2,8 m	
Channel 1 on/off, (non-floating contact)	-	
Channel 2 dim	-	
Push button input	Yes	
Motion detection by default	Yes	
Presence detection by setting	Yes	
Semi-automatic mode	Yes	
Adjustable sensitivity	Yes	
Lux switching on & off	Yes	
Separate sensitivity for active & passive mode	-	
Detection indication	Yes	
Setting indication	Yes	
Delay time, stepless	10 sec - 30 min	
Dimmer memory (last manual setting)	-	
Corridor function	-	
Auto burn-in of fluorescent tubes	-	
SETTING	1	
Control knob sensor	Yes	
Remote control	UNLCDHS	
Remote control, user	UHS5/UHS7	
GENERAL DATA		
Dimensions (diameter/depth mm)	76/65	
	,	
Product weight	0,16 kg	
Colour	White RAL 9003	
Guarantee	5 years	
ACCESSORIES		
Ceiling mounting bracket	MWS3A-DBB	
Wall mounting bracket	MWS3A-DBB-WBRKT	

Code Suffix	Region	MWS3-KNX
R2	Australia and all of Europe except: UK, France, Portugal, Germany, Switzerland, Austria, Slovak Republic, Republic of Ireland	760203
R3	France, Portugal, Switzerland	760204
R4	Germany, Austria, Slovak Republic	760205



ACCESSORIES

CEILING BRACKET, LARGE MWS3A-DBB ART. 760133



WALL BRACKET, LARGE MWS3A-DBB-WBRKT ART. 760080

All specifications are subject to change. For the latest version of this product leaflet, please visit www.auralight.com/products.

2016-02-16



