

Switch disconnecter 80A, size 02, 3-pole Front operating mechanism  
center Basic unit without handle Box terminal



Model	
product brand name	SETRON
product designation	3KD switch disconnecter
design of the product	Switch
display version / for switch position indicator door-coupling rotary operating mechanism	ON-OFF
design of the operating mechanism	Without handle
type of the driving mechanism	Front operating mechanism
type of the driving mechanism / motor drive	No
General technical data	
number of poles	3
type of device	fixed mounting
size of switch disconnecter	02
mechanical service life (switching cycles) / typical	100 000
electrical endurance (switching cycles)	
• at AC-23 A / at 690 V	6 000
• I <sub>2t</sub> value / of the fuse / at 400 V / maximum permissible	80 000 A <sup>2</sup> ·s

• I <sub>2t</sub> value / of the fuse / at 500 V / maximum permissible	80 000 A <sup>2</sup> ·s
• I <sub>2t</sub> value / of the gG fuse / at 690 V / maximum permissible	75 000 A <sup>2</sup> ·s
position / of the switch operating mechanism	central
overvoltage in percent / relative to the operating voltage / at AC / at 400, 500, 690 V / at 50/60 Hz	5 %
overvoltage category	III
degree of pollution	3

#### Voltage

insulation voltage	
• rated value	750 V
surge voltage resistance / rated value	8 kV

#### Supply voltage

operating current / at AC / rated value	80 A
operating voltage	
• at AC / at 50/60 Hz / rated value	690 V

#### Protection class

protection class IP	IP10
protection class IP	
• with closed switch / with cover or cable lug cover	IP10
• on the front	IP40

#### Dissipation

power loss [W]	
• with conventional rated thermal current / per pole	5 W
• with conventional rated thermal current / per device	5 W
• for rated value of the current / at AC / in hot operating state / per pole	14.8 W

#### Current

• operating current / at AC-23 A / at 690 V / rated value	30 A
• operating current / at AC-23 A / at 500 V / rated value	30 A
• operating current / at AC-23 A / at 400 V / rated value	75 A
• operating current / at AC-22 A / at 690 V / rated value	80 A
• operating current / at AC-22 A / at 500 V / rated value	80 A

• operating current / at AC-22 A / at 400 V / rated value	80 A
• operating current / at AC-21 A / at 400 V / rated value	80 A
• operating current / at AC-21 A / at 500 V / rated value	80 A
• operating current / at AC-21 A / at 690 V / rated value	80 A
• operating current / at AC-23 A / at 500 V / at 50/60 Hz / rated value / maximum	30 A
• operating current / at AC-22 A / at 500 V / at 50/60 Hz / rated value / maximum	80 A
• operating current / at AC-22 A / at 400 V / at 50/60 Hz / rated value / maximum	80 A
• operating current / at AC-22 A / at 690 V / at 50/60 Hz / rated value / maximum	80 A
• operating current / at AC-23 A / at 400 V / at 50/60 Hz / rated value / maximum	75 A
• operating current / at AC-23 A / at 690 V / at 50/60 Hz / rated value / maximum	30 A
continuous current	
• rated value	80 A
continuous current / of upstream fuse / at 500 V and 690 V / rated value	100 A
let-through current / of the fuse / at 400 V / maximum permissible	10 000 A
let-through current / of the fuse / at 500 V / maximum permissible	7 000 A
let-through current / of the gG fuse / at 690 V / maximum permissible	7 000 A

#### Main circuit

operating power	
• at AC-23 A / at 400 V / at 50/60 Hz / rated value	37 kW
• at AC-23 A / at 500 V / rated value	18.5 kW
• at AC-23 A / at 690 V / at 50/60 Hz / rated value	30 kW
operating current / rated value	80 A

#### Auxiliary circuit

number of connected NC contacts / for auxiliary contacts	0
number of connected NO contacts / for auxiliary contacts	0
number of connected CO contacts / for auxiliary contacts	0
number of CO contacts / for auxiliary contacts	0

number of NC contacts / for auxiliary contacts	2
number of NO contacts / for auxiliary contacts	2
<b>Suitability</b>	
suitability for use	
• main switch	Yes
• switch disconnecter	Yes
• EMERGENCY OFF switch	Yes
• safety switch	Yes
• maintenance/repair switch	Yes
<b>Product details</b>	
product feature / interlock	No
product component	
• trip indicator	No
• voltage trigger	No
• undervoltage release	No
• undervoltage release with leading contact	No
product extension / auxiliary switch	Yes
product extension / optional	
• motor drive	No
• voltage trigger	No
<b>Short circuit</b>	
short-circuit current making capacity (I <sub>cm</sub> )	
• for switch disconnecter / without fuse link / rated value / minimum	3.55 kA
conditional short-circuit current / with line-side fuse protection	
• at 500 V / by gG fuse / rated value	50 kA
• at 690 V / by gG fuse / rated value	50 kA
<b>Connections</b>	
type of connectable conductor cross-sections / for copper conductor	
• solid	1 x (4 ... 50) mm <sup>2</sup>
• finely stranded / with core end processing	1 x (4 ... 35) mm <sup>2</sup>
• stranded	1 x (4 ... 50) mm <sup>2</sup>
type of electrical connection	
• for main current circuit	box terminal
<b>Mechanical Design</b>	
height	110 mm
width	73 mm
depth	74 mm
mounting type	Screw fixing and standard rail mounting 35 mm

mounting type	
• front mounting with 4-hole attachment	No
• front mounting with central attachment	No
• rail mounting	Yes
mounting position	any
net weight	365 g

#### Environmental conditions

ambient temperature / during operation	
• minimum	-5 °C
• maximum	40 °C
ambient temperature / during storage	
• minimum	-25 °C
• maximum	55 °C

#### Certificates

reference code	
• acc. to DIN EN 61346-2	Q
• acc. to DIN EN 81346-2	Q

#### Further information

##### Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/lowvoltage/catalogs>

##### Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3KD0430-2LG20-3>

##### Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3KD0430-2LG20-3>

##### Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=3KD0430-2LG20-3](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3KD0430-2LG20-3)

##### CAX-Online-Generator

<http://www.siemens.com/cax>

##### Tender specifications

<http://www.siemens.com/specifications>



