



PERFORM 6500 LPG

PORTABLE POWER

Range 50Hz Perform

Product advantages

- Bicarburant LPG / Petrol
- Solid and compact frame
- Circuit Breaker
- Good value for money
- Oil level safety
- Entire group guaranteed 3 years

Accessories supplied as standards

- Funnel to drain
- Illustrates user and maintenance manual
- Plot of ground maintenance
- Ergonomic handles
- Thermal circuit breaker



This product is QUALIGEN certified. Defined by the SIMOTHERM and GIGREL professional organisations, the QUALIGEN charter is intended to provide a label for equipment compliant with current regulations (user safety, noise level, power, sales information, After Sales Service) in order to provide the highest level of quality of our and thus to guarantee the users safety.

PERFORM 6500 LPG

General specifications

Range	Perform
Frequency (Hz)	50
Max Power. (kW)	Att validation / 6.5
Max Power. (kVA)	At validation / 8.15
Nominal voltage (V)	230
Number of phase	Single phase
Acoustic pressure level Lw(A)	101
Noise level dB(A) à 1m	88
Noise level dB(A) à 7m	78

Engine specifications

Engine trademark	Kohler
Engine type	CH 440
Distribution	O.H.V.
Start	Launcher
Fuel	LPG / Gasoline
Oil guard	Yes
Capacity (cm3)	429
Oil capacity (L)	1.1

LPG / Gasoline specifications

	LPG	Gasoline
Autonomy	Following bottle used	2.8
Consumption (L/h)	Attente validation	2.6 L/h
Consumption (Kg/h)	Att validation	Att validation
Tank (L)	Following bottle used	7.3

Alternator specifications

Type	Without collar or brush
Regulation	Mechanical
Protection class	IP 23
Insulation class	Class H

Descriptif prises et coffrets

1 x 2P+T 230V 10/16A - disjoncteur + 1 x 2P+T 230V 32A – circuit breaker

Dimensions and weight

Lenght {cm}	81
Width {cm}	55.5
Height {cm}	59
Dry Weight {kgs}	96.5

Packaging

Packaging type	Box
Lenght (cm)	82
Width (cm)	56.5
Height (cm)	60
Pallet Type	120/80
Number of box by pallet	6
Pallet height (cm)	193

Options



R02	Differential boxes R02	This set includes a hour meter and a differential switch.
RKD1	RCCB	Kit of 2 plug-in RCCB adaptaters for domestic sockets.
RKS1	Maintenance kit	Each kit contains a bottle of oil, a spark plug, an air filter and a fuel filter.
RBH1	Bottles of oil	Box of 20 1l. Cans of oil (SAE 15W40)
RBH0-5	Bottles of oil	Box of 24 0.5l. cans of oil (SAE15W40)
R05M	Manual transfer switch	The manual changeover switch is used to connected and disconnecte a generating set manually to a domestic circuit when there is a power cut.
RKB1	Trolley kit	For generating sets and welding sets up to 6kW
RHO	Cover	Loose cover for storing and protecting generating sets.
RPM	Set of male plug	Male plugs for all models made up ofde : 2x16A/230V, CE17 : 1x16A/230V, 1x32A/230V and 1x16A/400V.
RPQ	Earth spike	For earthing your generating set. A 1m long galvanised spike, supplied with 2m of 10 mm ² thick cable.
RBAC	RBAC	Removable storage box.