



## DIESEL 10000 E SILENCE AVR

PORTABLE POWER

Generating Sets Range DIESEL

### PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Very Silent
- Connection interface equipped with an hour meter
- Hydrocarbons bulk tank

This genset is quiet and compact and features easy-to-reach components for simplified maintenance. The Mics MODYS control panel displays overspeed, starting failure, oil pressure, battery and temperature

### Range DIESEL

Both long run times and very long life for professional applications.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

## DIESEL 10000 E SILENCE AVR

### GENERAL SPECIFICATIONS

Range	DIESEL
Frequency (Hz)	50
Max power LTP (kW) *	9
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Fuel
Tank (L)	27
75% cons. (l/h) *	2.10
75% Autonomy (h) *	12.90
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	68

### ENGINE SPECIFICATIONS

Engine model	KOHLER DIESEL
Engine type	KD425-2
Distribution	Diesel O.H.V.
Start	Electrical
Oil Guard	Oui
Capacity (cm3)	851
Oil capacity (L)	1.80

### ALTERNATOR SPECIFICATIONS

Technology	Collar and brush
AVR Regulation	Yes
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 16A socket - circuit breaker + 1 230V 32A socket - circuit breaker + hour meter + indicator + MICS MODYS

### DIMENSIONS AND WEIGHT

Lenght (cm)	118.30
Width (cm)	67.30
Height (cm)	96
Dry Weight (kgs)	269

### PACKAGING

Packaging type	Box
Length (cm)	120
Width (cm)	69
Height (cm)	94
Weight (kg)	272
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0



## ACCESSORIES SUPPLIED



User and maintenance manual



Battery without maintenance



Lifting eye

## OPTIONS



R02B

### Differential protection

This set includes a differential switch, a hour meter, the plugs and a thermal circuit breaker.



RSTART

### Wireless remote

Remote control in order to start or stop the generating set until a distance of 50 meters (needs the installation of a MODYS control panel)



VERSO50

### Automatic start panel

Switches over automatically if the □ mains fails, 40A or 100A 1P or if the □ mains fails, 25A or 40A 3P (needs the installation of a MODYS control panel). Includes the battery charger.



R05M

### Manual changeover switch

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RKB5

### Trolley kit

Trolley kit with 1 handle and 2 solid tyres for Diesel 10000 E SILENCE et Diesel 15000 TE SILENCE gensets

no picture

RKDS3

### Maintenance kit for KOHLER engines

Maintenance kit for KOHLER KD425-2 engine.



RPM

### Set of male plugs

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ

### Earth spike

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm<sup>2</sup> cable.