


Surface-mounted home station



Specification	Order No.	Packing unit	PS	EAN
 <p>pure white glossy</p>	1250 112	1	18	4010337047391

Features

- Completely pre-assembled surface-mounted home station This facilitates fast and clean installation.
- Design diversity thanks to integration into the design line, allowing uniform appearance of door communication and electrical installation.
- Installation possible with or without frame.
- Easy installation with plug-in screw terminals on the mounting plate. Contact to the home station is established when the home station is attached to the mounting plate.
- Easy disassembly of the home station during renovation work.
- Mounting holes for installation.
- Signal transmission and power supply of home station via reverse-polarity-protected and short-circuit-proof 2-wire bus.
- Parallel connection of up to three home stations is possible (with power supply via the 2-wire bus).
- One-man start-up with easy start-up procedure.
- Ringtone differentiation for door call, internal call and floor call.
- Choice of five different ringtone melodies for separate assignment to specific call buttons.
- Speakerphone function (voice-controlled talk-back with echo and background noise suppression).
- Enforcement function for loud background noises during the voice connection.
- Eavesdropping prevention.
- Operating buttons with integrated LEDs for status display.

The operating buttons of the surface-mounted home station control the following functions in connection with the switching actuator or the flush-mounted switching actuator:

- Switching of lights and other functions.
- Control of the door opener.
- Setting the ringtone melody.
- Switching the ringtone on and off.
- Call acceptance.
- Activation of the enforcement function.
- Adjustment of ring tone and voice volume.

Technical data

Power supply:	DC 26 V \pm 2 V (via 2-wire bus)
Ambient temperature:	0 °C to +50 °C
Connections	
- 2-wire bus:	2x screw terminals

Illustrations are similar and may deviate from originals.

- Floor-call button: 2x screw terminals

Notes

- Installation without frame is possible.
 - A 2-gang cover frame without crossbar is required for installation with System 55 or Gira F100.
 - A frame is required for installation in a device box
 - This component enables door communication systems with up to 70 devices to be set up (e.g. 1 x built-in speaker, 5 x add-on modules for built-in speakers, 68 x surface-mounted home stations).
-

Dimensions in mm

System 55:	W 55	H 127	D 20
Gira F100:	W 70	H 142	D 20
