catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

## KNX power supply 640 mA uninterruptible

**GIRA** Data sheet



Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
DRA	1079 00	1	376.20	26	4010337009115

#### **Features**

- The uninterruptible power supply 640 mA generates the KNX system voltage.
- With integrated choke for de-coupling the bus line from the power supply.
- With connections for a lead-gel rechargeable accumulators for buffering KNX voltage in case of a mains failure.
- Up to two lead-gel rechargeable accumulators can be connected and charged via the uninterruptible power supply.
- The charging voltage is controlled depending on the temperature using a temperature sensor.
- The uninterruptible power supply has a zero-voltage 2-way switch for reporting a fault (e.g. mains failure, battery failure, overload, or short circuit).

#### **Technical data**

Primary rated voltage: AC 230 V, 50 / 60 Hz

Secondary rated voltage: DC 28 to 31 V SELV

Secondary rated current: 640 mA, short-circuit-proof

Zero-voltage 2-way switch: AC 230 V, 6A

Zero-voltage 2-way switch: DC 12/24 V, 4 A

Connections

- KNX: Connection and junction terminal

- Load: Screw terminals

Connections: max. 4 mm<sup>2</sup>

### **Notes**

- Connection is made via KNX bus connection or junction terminals (no data rail required).
- Recommendation: Overvoltage protection for Gira KNX products.

# **GIRA** Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

- Overvoltage diverter BUStector BT 24, manufacturer: DEHN + SÖHNE, Article No. 925001.				
Scope of supply - KNX connection and junction terminal included in the scope of supply.				
<b>Dimensions</b> Modular widths (MW):	8			