

* IK2

Specifications



ETI Code	001701202
Description	* IK2
Class name	Fuse link base
Product group accessories	Fuse bases type PLNV
To use with	2PLNV 2
Type accessories	Protection cap

[Online product page](#)

Other documentation

[Instruction manual](#)
[Technical data catalogue](#)
[COM_ETISTORE_ITEM_DOCTYPE_I](#)
[nstruction manual](#)
[CE declaration](#)




ETIM international clasification

Classification	EC001660
Class name	Accessories for Low Voltage HRC fuse bases
Construction size	NH2


Dimension drawing

DIMENSION DRAWINGS


PLNV - 00/1




2PLNV - 1/1, 2PLNV - 2/1, 2PLNV - 3/1



PLNS - 00N



2PLNS - 1N, 2PLNS - 2N



* - fuse-base PLNV - 00/3 fasten with four screws minimally (distance between holes 25 x 68mm)

	2PLNS - 1N	2PLNS - 2N
B	175,6	200
C	200	230
D	25	30

Fuse Base PLNV

Type	A	B	C	D	E	F	G	H	I	J
2PLNV - 1/1	140	175	200	25	-	-	76	82	-	M10
2PLNV - 2/1	154	200	230	30	-	-	83	87	-	M10
2PLNV - 3/1	154	210	250	30	-	-	91	95	-	M12
2PLNV - 1/3	140	175	200	25	65	187	76	82	103	M10
2PLNV - 2/3	154	200	230	30	65	187	83	87	112	M10
2PLNV - 3/3	154	210	250	30	80	217	91	95	126	M12