

GENIE

GENIE 11W WW E27 220-240V 1PF

Functional non-covered Energy saving lamp, with money saving high quality light and compact design. This lamp is small enough to fit neatly wherever you need extra bright light at home, enables easy replacement of most incandescent lamp all the way.

Product data

• General Characteristics

Cap-Base Bulb	E27 Stick
Nominal Lifetime	10000 hr
Rated Lifetime	10000 hr
(hours)	
Rated Lifetime	10 an
(years)	

• Light Technical Characteristics

Color Code Color Rendering Index	827 [CCT of 2700K] 82 Ra8
Color Designation (text)	Warm White
Color Temperature	2700 K
Color Temperature	2700 K
Technical	
Luminous flux lamp	600 Lm
Rated Luminous Flux	600 Lm
Luminous Efficacy	55 Lm/W
Lamp	
Lumen Maintenance	88 %
2000h	
Lumen Maintenance	70 %
6000h	
LLMF - end nominal	65 %
lifetime	
Chromaticity Coor-	463 -
dinate X	
Chromaticity Coor-	420 -
dinate Y	

• Electrical Characteristics

Rated Wattage 11.0 W

Lamp Wattage Power Factor 0.6 -220-240 V Voltage Lamp Current mA 80 mA Line Frequency 50/60 Hz Dimmable No Wattage Equivalent Starting Time 50 W 0.3 s Warm-up Time to 5 (min), 40 (max) s 60% Light Outp

11 W

• Environmental Characteristics

Energy Efficiency	A
Label (EEL)	
Mercury (Hg)	1.5 (nom), 2.0 (max) mg
Content	
Energy consumption	11 kWh
kWh/1000h	

Measuring Conditions

Switching cycle

• Product Dimensions

Overall Length C Diameter D Width F

117.0 (max) mm 35.0 (max) mm 44.4 (max) mm

10000X

• Product Data

Order code Full product code Full product name Order product name 929689113501 929689113501 GENIE 11W WW E27 220-240V 1PF GENIE 11W WW E27 220-240V 1PF/6



GENIE

Pieces per pack1Packing configuration6Packs per outerbox6Bar code on pack -8711500801197EAN18711500801197

Warnings and Safety

• Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic

Dimensional drawing

bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.

Compact fluorescent lamps have to be treated as special waste, they
must be taken to your local waste facilities for recycling. The
European Lighting Industry has set up an infrastructure, capable of
recycling mercury, other metals, glass etc.

GENIE 11W WW E27 220-240V 1PF

Product	C (Max)	D (Max)	F (Max)
Econ Genie Erp 11W/827 E27 220-240V	117.0	35.0	44.4



E27



© 2014 Koninklijke Philips N.V. (Royal Philips) All rights reserved.

Specifications are subject to change without notice. Trademarks are the property of Koninklijke Philips N.V. (Royal Philips) or their respective owners.

www.philips.com/lighting