

9040 Phase Rotation Indicator



Technical Data

Features

- Large display to easily determine field rotation
- Indication for all three phases
- CAT III 600 V
- Included accessories: test leads and probes, alligator clips
- Two-year warranty

Phase rotation indicator for industrial applications

The Fluke 9040 Phase Rotation Indicator is a portable hand-held instrument designed to detect the rotary field of three-phase systems. With three test leads, this rugged tester easily determines a clockwise or counterclockwise direction.

Specifications

Environmental

Operating temperature: 0 °C to +40 °C

Pollution degree: 2

Type of protection: IP 40

Mechanical specifications

Size (HxWxD): 124 mm x 61 mm x 27 mm

Weight: 200 g

Safety specifications

Electrical safety:

IEC 61010/EN 61010,

IEC 61557-7/EN 61557-7

Maximum operating voltage (U_{me}): 690 V

Protection levels: CAT III 600 V to ground

Electrical specifications

Power supply: From unit under test

Determine rotary field direction

Nominal voltage: 40 to 690 V ac

Frequency range (f_n): 15 to 400 Hz

Current Pickup: 1 mA

Nominal test current (in per phase): 1 mA

Warranty: Two-years

Included

3 self-retaining test probes (black)

Alligator Clip

Users Manual



Ordering Information

9040 Phase Rotation Indicator